

Vinyl Fence Light Instructions



Materials Needed:

- Power Drill with 7/16" drill bit
- Phillips Head Screwdriver
- Hammer

500 Principio Parkway W.
Unit 300
North East, MD 21901

(410) 287-3232
sales@ilightingLED.com
www.ilightingLED.com

- 1 Install the power supply with the instructions given.
- 2 Turn the system on by removing the photo eye (unplug the photo eye micro-connector from the power supply)
- 3 Pre-wire the upper fence rail with the 10' connector cables.
- 4 Plug the other end of the T-cable into the 10' connector cables.
- 5 Locate and drill a 7/16" hole in the post where the light will be mounted.
- 6 Attach the light fixture to the black connector on the T-cable's 30" lead.
- 7 Continue to connect all the lights together by plugging together each connector cable.
- 8 Reconnect the photo eye when installation is complete.

*****To ensure a water tight seal, push connectors together.*****